NPort® IA5000A Series

-1, 2, and 4-port serial device servers for industrial automation



- > Enhanced surge protection for LAN/serial/power
- > 2 kV isolation for serial signals (isolation models)
- > Screw-type terminal blocks for secure power/serial connections
- > C1D2, ATEX, and IECEx certified for harsh industrial environments
- > Cascading Ethernet ports for easy wiring
- > Redundant DC power inputs
- > Warning by relay output and email
- > -40 to 75°C operating temperature range (T models)




Overview

The NPort IA5000A series device servers are designed for connecting industrial automation serial devices, such as PLCs, sensors, meters, motors, drives, barcode readers, and operator displays. The device servers are built solid with a metal housing, screw connectors, and

provide full surge protection. The NPort IA5000A series device servers are extremely user-friendly, making simple and reliable serial-to-Ethernet solutions possible.

Cascading Ethernet Ports Make Wiring Easy (10/100BaseTX models only)


The NPort IA5000A series device servers each have two Ethernet ports that can be used as Ethernet switch ports. One port connects directly to the network or server, and the other port can be connected to either another NPort IA device server or another Ethernet device. The dual Ethernet ports help reduce wiring costs by eliminating the need to connect each device to a separate Ethernet switch.



Redundant Power Inputs

The NPort IA5000A series device servers have two power inputs that can be connected simultaneously to live DC power sources. If one power source fails, the other source takes over automatically. Redundant power inputs help ensure uninterrupted operation of your device server.


Dual Power Inputs



Relay Output Warning and E-mail Alerts

The built-in relay output can be used to alert administrators when the network is down, when power failure occurs, or when there is a change in the DCD or DSR serial signals. An e-mail warning can also be issued when an abnormality is detected. These functions are valuable tools that enable maintenance engineers to react promptly to emergency situations.

Power Failure Alarm



Surge Protection for Serial, LAN, and Power

Moxa's leading-edge surge immunity solution, which is applied to the NPort® IA5000A's serial, power, and Ethernet lines, is tested and proven compliant with IEC 61000-4-5. This advanced surge protection

provides a robust serial-to-Ethernet solution that can protect electrical devices from voltage spikes and resist electrical interference, such as in oil, gas, and power automation applications.

Industrial-Grade Certification

To ensure safe and reliable operation in industrial environments, the NPort® IA5000A device servers have obtained various industrial certifications, including an IP30 rating for mechanical protection and UL 508 safety certification for industrial control equipment. In

addition, these device servers are UL/cUL listed (for Class 1, Division 2, Groups A,B,C,D), ATEX Class 1 Zone 2, and IECEx compliant for use in hazardous locations.

: Specifications

Ethernet Interface

Number of Ports: 2 Speed: 10/100 Mbps, auto MDI/MDIX Connector: 8-pin RJ45 Magnetic Isolation Protection: 1.5 kV built-in Ethernet Line Protection: 1 kV (level 2) surge protection

Serial Interface

Number of Ports: NPort IA5150A: 1 NPort IA5250A: 2 NPort IA5450A: 4

Serial Standards: RS-232/422/485

Connector:

NPort IA5150A: DB9 for RS-232, terminal block for RS-422/485 NPort IA5250A/IA5450A: DB9 for RS-232/422/485

Serial Line Protection:

• 2 kV isolation protection for isolation models

1 kV (level 2) surge protection

RS-485 Data Direction Control: ADDC $\ensuremath{\mathbb{B}}$ (Automatic Data Direction Control)

Serial Communication Parameters

Data Bits: 5, 6, 7, 8 Stop Bits: 1, 1.5, 2 Parity: None, Even, Odd, Space, Mark Flow Control: RTS/CTS and DTR/DSR (RS-232 only), XON/XOFF Baudrate: 50 to 921.6 kbps

Serial Signals

RS-232: TxD, RxD, RTS, CTS, DTR, DSR, DCD, GND RS-422: Tx+, Tx-, Rx+, Rx-, GND RS-485-4w: Tx+, Tx-, Rx+, Rx-, GND RS-485-2w: Data+, Data-, GND

Software

Network Protocols: ICMP, IPv4, TCP, UDP, DHCP, BOOTP, Telnet, DNS, SNMP, HTTP, SMTP, SNTP, IGMP, ARP Configuration Options: Web Console, Serial Console, Telnet Console, Windows Utility Windows Real COM Drivers: Windows 95/98/ME/NT/2000, Windows XP/2003/Vista/2008/7/8/8.1/10 (x86/x64), Windows 2008

R2/2012/2012 R2 (x64), Windows Embedded CE 5.0/6.0, Windows XP Embedded

Fixed TTY Drivers: SCO Unix, SCO OpenServer, UnixWare 7, QNX 4.25, QNX 6, Solaris 10, FreeBSD, AIX 5.x, HP-UX 11i, Mac OS X Linux Real TTY Drivers: Linux 2.4.x, 2.6.x, 3.x

Physical Characteristics

Housing: Metal Weight: NPort IA5150A: 475 g (1.05 lb) NPort IA5250A: 485 g (1.07 lb)

NPort IA5450A: 560 g (1.23 lb) Dimensions:

NPort IA5150A/IA5250A: 36 x 105 x 140 mm (1.42 x 4.13 x 5.51 in) NPort IA5450A: 45.8 x 134 x 105 mm (1.8 x 5.28 x 4.13 in)

Environmental Limits

Operating Temperature: Standard Models: 0 to 60°C (32 to 140°F)

Wide Temp. Models: -40 to 75°C (-40 to 167°F) **Storage Temperature:** -40 to 75°C (-40 to 167°F)

Ambient Relative Humidity: 5 to 95% (non-condensing)

Power Requirements

Input Voltage: 12 to 48 VDC

Input Current:

NPort IA5150A: 220 mA @ 12 VDC NPort IA5150AI: 225 mA @ 12 VDC NPort IA5250A: 250 mA @ 12 VDC NPort IA5250AI: 290 mA @ 12 VDC NPort IA5450AI: 374 mA @ 12 VDC NPort IA5450AI: 512 mA @ 12 VDC

Standards and Certifications

Safety: UL 508

 Hazardous Location: UL/cUL Class I Division 2 Groups A/B/C/D, ATEX

 Class I Zone 2, IECEx

 EMC: EN 55032/24

 EMI: CISPR 32, FCC Part 15B Class A

 EMS:

 IEC 61000-4-2 ESD: Contact: 6 kV; Air: 8 kV

 IEC 61000-4-3 RS: 80 MHz to 1 GHz: 10 V/m

 IEC 61000-4-4 EFT: Power: 4 kV; Signal: 2 kV

 IEC 61000-4-5 Surge: Power: 2 kV; Signal: 1 kV

 IEC 61000-4-6 CS: 150 kHz to 80 MHz: 10 V/m; Signal: 10 V/m

 IEC 61000-4-8 PFMF

 Freefall: IEC 60068-2-32

 Vibration: IEC 60068-2-6

 Shock: IEC 60068-2-27

Reliability

Alert Tools: Built-in buzzer and RTC (real-time clock) Automatic Reboot Trigger: Built-in WDT (watchdog timer)


Dimensions

MTBF (mean time between failures) Time: 262,805 hrs Standard: Telcordia (Bellcore) Standard TR/SR Warranty Warranty Period: 5 years Details: See www.moxa.com/warranty


Pin Assignment

	PIN	RS-232	RS-422/RS-485-4w	RS-485-2w
RS-232/422/485	1	DCD	TxD-(A)	-
DB9 male port	2	RXD	TxD+(B)	-
12345	3	TXD	RxD+(B)	Data+(B)
	4	DTR	RxD-(A)	Data-(A)
	5	GND	GND	GND
	6	DSR	-	-
6789	7	RTS	-	-
	8	CTS.	_	_

RS-422/485 Terminal



PIN	RS-422/RS-485-4w	RS-485-2w
1	TxD+(B)	-
2	TxD-(A)	-
3	RxD+(B)	Data+(B)
4	RxD-(A)	Data-(A)
5	GND	GND



: Ordering Information

Available Models

NPort IA5150A: 1-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 0 to 60°C operating temperature

NPort IA5150AI: 1-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation, 0 to 60°C operating temperature

NPort IA5250A: 2-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 0 to 60°C operating temperature

NPort IA5250AI: 2-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation, 0 to 60°C operating temperature

NPort IA5450A: 4-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 0 to 60°C operating temperature

NPort IA5450AI: 4-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation protection, 0 to 60°C operating temperature

NPort IA5150A-T: 1-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, -40 to 75°C operating temperature

NPort IA5150AI-T: 1-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation, -40 to 75°C operating temperature

NPort IA5250A-T: 2-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, -40 to 75°C operating temperature

NPort IA5250AI-T: 2-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation, -40 to 75°C operating temperature

NPort IA5450A-T: 4-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, -40 to 75°C operating temperature

NPort IA5450AI-T: 4-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation protection, -40 to 75°C operating temperature

IECEx Models

NPort IA5150A-IEX: 1-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, IECEX, 0 to 60°C operating temperature

NPort IA5150AI-IEX: 1-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation, IECEx, 0 to 60°C operating temperature

NPort IA5250A-IEX: 2-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, IECEx, 0 to 60°C operating temperature

NPort IA5250AI-IEX: 2-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation, IECEx, 0 to 60°C operating temperature

NPort IA5450A-IEX: 4-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, IECEX, 0 to 60°C operating temperature

NPort IA5450AI-IEX: 4-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation protection, IECEx, 0 to 60°C operating temperature

NPort IA5150A-T-IEX: 1-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, IECEx, -40 to 75°C operating temperature

NPort IA5150AI-T-IEX: 1-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation, IECEx, -40 to 75°C operating temperature

NPort IA5250A-T-IEX: 2-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, IECEx, -40 to 75°C operating temperature

NPort IA5250AI-T-IEX: 2-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation, IECEx, -40 to 75°C operating temperature

NPort IA5450A-T-IEX: 4-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, IECEx, -40 to 75°C operating temperature

NPort IA5450AI-T-IEX: 4-port RS-232/422/485 industrial automation device server with serial/LAN/power surge protection, two 10/100BaseT(X) ports with single IP, 2 kV isolation protection, IECEx, -40 to 75°C operating temperature

Optional Accessories (can be purchased separately)

Mini DB9F-to-TB: DB9 female to terminal block adapter for RS-422/485 applications WK-36-02: Wall-mounting kit for the NPort IA5150A/IA5250A

WK-51-01: Wall-mounting kit for the NPort IA5450A

Package Checklist

- 1 NPort IA5000A series device server
- Documentation and software CD
- Quick installation guide (printed)
- Warranty card

Power Accessory Selection Guide

Barrel Plug Type O/P		Locking Barrel Plug 12 VDC 0.5 A, 100 to 240 VAC (Switch-Mode)						
Appearance								
Model Nam	ne	PWR-12050-WPUSJP-S1	PWR-12050-WPEU-S1	PWR-12050-WPAU-S1	PWR-12050-WPUK-S1	PWR-12050-WPCN-S1		
	NPort 5110	-	-	-	-	-		
	NPort 5130	-	-	-	-	-		
	NPort 5150	-	-	-	-	-		
	NPort 5110A	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5130A	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
1 Port	NPort 5150A	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	DE-211	-	-	-	-	-		
	DE-311	-	-	-	-	-		
	NPort P5150A	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort W2150A	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort Z2150/Z3150	✓	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5210	-	-	-	-	-		
2 Ports	NPort 5230	-	-	-	-	-		
	NPort 5232	-	-	-	-	-		
	NPort 5232I	-	-	-	-	-		
	NPort 5210A	✓	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5230A	✓	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5250A	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort W2250A	√	\checkmark	\checkmark	\checkmark	\checkmark		

Barrel Plug Type O/P		Non-Locking Barrel Plug 12 VDC 0.5 A, 100 to 240 VAC (Switch-Mode)						
Appearance		E E En En En						
Model Nar	ne	PWR-12050-WPUSJP-S2	PWR-12050-WPEU-S2	PWR-12050-WPAU-S2	PWR-12050-WPUK-S2	PWR-12050-WPCN-S2		
	NPort 5110	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5130	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
1 Port	NPort 5150	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5110A	-	-	-	-	-		
	NPort 5130A	-	-	-	-	-		
	NPort 5150A	-	-	-	-	-		
	DE-211	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	DE-311	✓	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort P5150A	-	-	-	-	-		
	NPort W2150A	-	-	-	-	-		
	NPort Z2150/Z3150	-	-	-	-	-		
	NPort 5210	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
2 Ports	NPort 5230	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5232	✓	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5232I	✓	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5210A	-	-	-	-	-		
	NPort 5230A	-	-	-	-	-		
	NPort 5250A	-	-	-	-	-		
	NPort W2250A	-	-	-	-	-		

Power Accessory Selection Guide

Barrel Plug Type O/P		Non-Locking Barrel Plug 12 VDC 1.25/1.5 A, 100 to 240 VAC						
Appearance		Ŕ			W.	the r		
Model Na	ne	PWR-12125-USJP-S1	PWR-12150-EU-S2	PWR-12150-AU-S2	PWR-12150-UK-S2	PWR-12125-CN-S1		
	NPort 5410	√	√	✓	√	\checkmark		
	NPort 5430	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
4 Ports	NPort 5430I	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5450	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5450I	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark		
	NPort 5610-8	-	-	-	-	-		
	NPort 5630-8	-	-	-	-	-		
	NPort 5650-8	-	-	-	-	-		
	NPort 5650-8-M-SC	-	-	-	-	-		
	NPort 5650-8-S-SC	-	-	-	-	-		
	NPort 5610-8-DT	-	-	-	-	-		
8 Ports	NPort 5610-8-DT-J	-	-	-	-	-		
	NPort 5650-8-DT	-	-	-	-	-		
	NPort 5650-8-DT-J	-	-	-	-	-		
	NPort 5650I-8-DT	-	-	-	-	-		
	NPort 5610-8-DTL	-	-	-	-	-		
	NPort 5650-8-DTL	-	-	-	-	-		
	NPort 5650I-8-DTL	-	-	-	-	-		
	NPort 5610-16	-	-	-	-	-		
16 Ports	NPort 5630-16	-	-	-	-	-		
	NPort 5650-16	-	-	-	-	-		

Barrel Plug Type		Locking Barrel Plug						
0/P 12 VDC 2 A, 100 to 240 VAC (desktop type)			10A/250V Power Cord, 183 cm					
Plug Type Must accompany with US JP EU AU				AU	ик	CN		
Appearanc	28	and and						
Model Nar	ne	PWR-12200-DT-S1	PWC-C13US-3B-183	PWC-C13JP-3B-183	PWC-C13EU-3B-183	PWC-C13AU-3B-183	PWC-C13UK-3B-183	PWC-C13CN-3B-183
	NPort 5410	-	-	-	-	-	-	-
	NPort 5430	-	-	-	-	-	-	-
4 Ports	NPort 5430I	-	-	-	-	-	-	-
	NPort 5450	-	-	-	-	-	-	-
	NPort 5450I	-	-	-	-	-	-	-
	NPort 5610-8	-	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5630-8	-	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5650-8	-	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5650-8-M-SC	-	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5650-8-S-SC	-	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5610-8-DT	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
8 Ports	NPort 5610-8-DT-J	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5650-8-DT	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5650-8-DT-J	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5650I-8-DT	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5610-8-DTL	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5650-8-DTL	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5650I-8-DTL	✓	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5610-16	-	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
16 Ports	NPort 5630-16	-	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark
	NPort 5650-16	-	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark	\checkmark

MOXA